Non-incendive Mesa Rugged Notepad

Non-incendive Approval

The non-incendive Mesa Rugged Notepad™ from Juniper Systems, Inc. is MET Laboratory approved Non-Incendive Class I Div 2 per approval standard UL 1604 CSA 213 in the U.S. and Canada.



E113334

The non-incendive Mesa may be used in hazardous locations where ignitable concentrations of flammable gases, vapors or liquids are not part of the normal environment but can become so under unusual circumstances.

Model	MSA Series
Electrical Rating	+12VDC, 1.5A
Battery Type	Li-lon (only use the batteries specified in the Mesa Owner's Manual, P/N 20545)
Class, Division, Groups	Class I Division 2 Groups A, B, C, D T4

Read This Document

Read this document to learn how to safely operate the non-incendive Mesa Rugged

Notepad in potentially hazardous locations.

This addendum is a supplement to the owner's manual that came with the Mesa. Refer to the owner's manual for details on how to use the Mesa.



Note: The Mesa Owner's Manual is also available on our website at www.junipersys.com.

P/N 23339-00. Copyright December 2011, Juniper Systems, Inc. All rights reserved. Information is subject to change without notice. Mesa Rugged Notepad is a trademark of Juniper Systems, Inc.

Using the Mesa Rugged Notepad (!) in a Hazardous Location

The following rules must be followed to maintain the MET Laboratory approved non-incendive standard and to prevent the possibility of serious injury.

Warning: Explosion hazard – In hazardous locations:

- Do not dock the Mesa
- Do not change or charge batteries
- Do not insert or remove cards
- Do not connect or disconnect any device or cable

In hazardous locations the connector protector and battery doors must be in place as indicated below:



Avertissement : risque d'explosion – Dans des zones dangereuses:

- N'amarrez pas l'unité, ne changez pas et ne chargez pas les batteries, n'insérez et ne retirez pas de cartes et n'établissez ni ne rompez aucune connexion
- Les caches de protection des ports et des batteries doivent toujours rester installés



tel: 435.753.1881 | web: www.junipersys.com 1132 W. 1700 N. Logan, UT 84321